

Date		Project	
Type		Part Number	

**PRIME R** ALL-IN-ONE PERFORMANCE LIGHTING

# EMERGENCY Series

## 40W Emergency Driver

The RENO-EM-40RM meets Standard CSA C22.2 NO.141, UL924 and is designed for use with our UFO Highbay fixtures with 0-10V dimmable LED Drivers. It allows the UFO highbay to be used for both normal and emergency operations.

This emergency LED driver has the following features: Over-Voltage Protection, Short-Circuit Protection, Over-load Protection, and Open-Circuit Protection. Equipped with a Built-in integrated junction box and a wireless remote control for optional emergency testing.



### PRODUCT FEATURES

- UL listed for factory and field installation Standard of CSA C22.2 NO.141, UL9240 Flicker-free LED driver
- CEC Title 20 Compliant
- Constant power output
- Battery protections: over charge, over discharge, short circuit protection
- Compatible with a wide variety of LED fixtures and AC drivers
- Operating Temperature: 5°C to +50°C (41°F to 122°F)
- 5 year warranty

### KEY SPECIFICATIONS

<b>Input Voltage</b>	100-347V 50/60Hz
<b>Input Current</b>	200mA
<b>Input Power</b>	15W Max
<b>Output Voltage</b>	170VDC
<b>Output Power</b>	40W
<b>Recharge Time</b>	48 Hours
<b>Discharge Time</b>	90 Minutes
<b>Charging Current</b>	≤250mA
<b>Applications</b>	Commercial, Warehouse, Retail Facilities

## SPECIFICATIONS

Order#	Model	Wattage	Input Voltage	Discharge Time	Recharge Time	Battery Type
R83005	RENO-EM-40RM	40W	100-347V	90 Minutes	48hrs	Li-ion Battery

## DIMENSIONS

